

Super Dynamic Weather Resistant HD Network Camera WV-SW316L WV-SW316

Preliminary



HD / 1,280 x 960 H.264 Network Camera featuring Super Dynamic

Key Features

- 720p HD images up to 30 fps
- Newly developed 1.3 Megapixel high sensitivity MOS Sensor
- Multiple H.264 (High profile) streams and JPEG streams ensure simultaneous real time monitoring and high resolution recording by "UniPhier®", Panasonic's proprietary System LSI platform.
- Full frame (Up to 30 fps) transmission at 1,280 x 960 image size
- Super Dynamic and ABS (Adaptive Black Stretch) technologies deliver 128x wider dynamic range compared to conventional cameras.
- Face Super Dynamic Range technology ensures clear face image.
- H.264 and MPEG-4 are selectable for system migration.
- High sensitivity with Day/Night(IR) function:
 WV-SW316L: 0.3 lx (Color), 0 lx (B/W) at F1.3 (Wide) when the IR LED is lit
 WV-SW316: 0.3 lx (Color), 0.05 lx (B/W) at F1.3 (Wide)
- Motorized varifocal lens equipped:
 The zoom ratio can be changed and adjusted to an optional photographic area through the operation buttons on this unit and the setup menu.
- IR LED equipped: The equipped infrared LED makes it possible to take pictures at zero lx.(WV-SW316L)
- VIQS (Variable Image Quality on Specified area) technology allows the designated area to retain higher image quality while the excluded area will have a decreased image quality, which enables to use lower image file size and bit rate.
- ABF (Auto Back Focus) ensures easy installation.
- Digital Noise Reduction: 3D-DNR ensures noise reduction in various conditions.
- Electronic sensitivity enhancement: Auto (Up to 16x) / OFF
- Up to 6.4x Extra Optical Zoom under VGA resolution.
 3.1-10 mm, 3.2x vari-focal auto iris lens (6.2-20 mm, 6.4x with Extra Optical Zoom at VGA)
- VMD (Video Motion Detector) with 4 programmable detection areas, 15 steps sensitivity level and 10 steps detection size
- Face detection function detects the position of human face and the information is sent by XML or video stream.
- Meta data for VMD is supplied to work with the WJ-NV200 /WJ-ND400 playback VMD function.
- Privacy Zone can mask up to 2 private areas, such as house windows and entrances/exits.
- Alarm sources including 1 terminal input, VMD and Panasonic alarm command can trigger actions such as SDHC/SD memory recording, FTP image transfer, E-mail notification, Indication on browser, Alarm terminal output, and Panasonic protocol output.

- Full duplex bi-directional audio allows interactive communication between camera site and monitoring site.
- JPEG image compression ratio can be changed by alarm so that higher quality image can be provided.
- Prioritized stream control: One of the video streams can be prioritized when multiple recorders or client PCs are accessing the camera so that the recorder or the client PC can maintain the frame rate.
- SDHC/SD Memory card slot for manual recording (H.264 / JPEG), alarm recording (H.264 / JPEG) and backup upon network failure (JPEG)
- H.264/MPEG-4 max. bit rate/client and Total bit rate control allows flexible network traffic management. Frame rate priority mode controls bit rate and compression ratio to provide the specified frame rate.
- Multi-language: English / Italian / French / German / Spanish / Russian / Chinese / Japanese
- IPv4/IPv6 protocol supported
- Supports SSL, DDNS (viewnetcam, RFC2136)
- Still images (JPEG) can be viewed on mobile phones via Internet.
- ONVIF compliant model
- Analog Monitor output for easier installation
- IP66 rated water and dust resistant. Compatible with IEC60529 measurement standard.

Standard Accessories

Installation Guide	Camera mount bracket
*1 The CD-ROM contains the operating instructions (PDFs) *2 This label may be required for network management. The network administrator shall retain the code label.	and different kinds of tool software programs.

Optional Accessory

Adapter Box WV-Q120



Specifications

TV System Camera	Image Senso		NTSC PAL 1/3 type MOS Sensor	
	Effective Pixels		Approx. 1.3 megapixels	
	Scanning Mo		Progressive scan 4.80 mm (H) x 3.60 mm (V) (3/16"(H) x 5/32"(V))	
	Scanning Area Minimum Illumination		W-SW316L: Color: 0.3 lx, B/W: 0 lx at F1.3 (Shutter: 1/30 s, AGC: High, when the IR LED is lit	
			Color: 0.019 lx, at F1.3 (Shutter: 16/30 s, AGC: High)	
			WV-SW316: Color: 0.3 lx, B/W: 0.05 lx at F1.3 (Shutter: 1/30 s, AGC: High),	
	10.150.11.1.		Color: 0.019 lx, B/W: 0.003 lx at F1.3 (Shutter: 16/30 s, AGC: High)	
	IR LED Light	tion distance	WV-SW316L: Off/Auto(High/Mid/Low)	
	IR LED irradiation distance White Balance Light Control Mode		WV-SW316L: 15 m (49.21 feet) AWC (2,000 – 10,000 K), ATW1 (2,700 ~ 6,000 K), ATW2 (2,000 ~ 6,000 K) Outdoor: Automatic integration of ALC and ELC Indoor [50 Hz]: Automatic integration of ALC and ELC (up to 1/100 s)	
			Indoor [60 Hz]: Automatic integration of ALC and ELC (up to 1/120 s) Fix shutter: 1/30, 3/100, 3/120, 2/100, 2/120, 1/100, 1/120,	
	Shutter Speed	t		
	·		1/250,1/500, 1/1,000, 1/2,000, 1/4,000, 1/10,000 (only at Super-Dynamic Of	
Super Dynamic			ON / OFF	
	Face Super Dy		ON / OFF (Only at Super Dynamic: ON) ON / OFF (Only at Super Dynamic: OFF)	
Adaptive Black Stretch AGC Electronic Sensitivity UP Day & Night (IR)		Collecti	ON (LOW, MID, HIGH) / OFF	
		sitivity UP	OFF / AUTO (Max. 2x (2/30 s), 4x (4/30 s), 6x (6/30 s), 10x (10/30 s), 16x (16/30 s) Mode: AUTO1 / AUTO2 / ON / OFF, Level:High / Low, with external control 52 dB typ. (Super Dynamic: On, Light control mode: indoor scene)	
)		
	Dynamic Range			
	Digital Noise Re		High / Low 4 areas, Sensitivity: 15 steps, Detection size: 10 steps Up to 2 zones, Gray ON / OFF List to 90 characters (slobacumaris characters, marks)	
	Video Motion D	etection		
	Privacy Zone			
	VIQS Camera Title (C	ISD)		
	Focus Adjustm		Up to 20 characters (alphanumeric characters, marks) ABF / MANUAL	
Lens	Focal Length		3.1 mm ~ 10 mm, 3.2x (6.2 mm ~ 20 mm, 6.4x with extra optical zoom (at VGA))	
	Angular Field o		H: 27.7° (TELE) ~ 100.3° (WIDE), V: 20.8° (TELE) ~ 73.6° (WIDE)	
	Maximum Aperture Ratio		1:1.3 (WIDE) ~ 1:3.0 (TELE)	
	Focusing Rang	e	0.3 m ~ ∞	
Adjusting A	ngle		Horizontal: ±100° (Camera mount bracket)	
Browsor GIII	Camera Contro	ı	Vertical: +30°, -90° (Camera mount bracket) Brightness, AUX ON / OFF	
Diowael GUI	Display Mode		Spot, Quad: Image from 16 cameras can be displayed in 4 different Quad	
	_ lopia, would		screens or 16 split screen (JPEG only). 20 characters camera title available.	
	Digital Zoom		1x, 2x, 4x controlled by browser GUI	
	Camera Title		Up to 20 alphanumeric characters	
	Clock Display		Time: 12H/24H, Date: 5 formats on the browser, Summer time (Manual)	
	Alarm Control		Reset	
	One Shot Capture		A still picture will be displayed on a newly opened window.	
	Audio		Mic (Line) Input: ON / OFF Volume adjustment: Low / Middle / High, Audio Output: ON / OFF Volume adjustment: Low / Middle / High	
	SD Memory D	ata Download	Still or motion Images recorded in the SDHC/SD memory	
	SD Memory Data Download		card can be downloaded.	
	GUI/Setup Menu Language		English, French, Italian, Spanish, German, Russian, Chinese, Japanese	
	System Log		Up to 100 (Internal), Up to 4,000 (SDHC/SD memory when therecording format is set to JPEG.) error logs	
	Supported OS 11 2		Microsoft® Windows® 7 Professional 64 bit/32 bit,	
			Microsoft® Windows Vista® Business SP1 32 bit,	
	Supported Browser		Microsoft® Windows® XP Professional SP3	
			Windows® Internet Explorer® 8.0 32 bit (Microsoft® Windows® 7	
			Professional 64 bit/32 bit), Windows® Internet Explorer® 7.0	
			(Microsoft® Windows Vista® Business SP1 32 bit), Microsoft® Internet Explorer® 6.0 SP3 (Microsoft® Windows® XP Professional SP3	
Network	Network IF		10Base-T / 100Base-TX, RJ-45 connector	
	Image Resolution *4	Aspect ratio: [4:3]	H.264: 1,280 × 960 / VGA (640 × 480) / QVGA (320 × 240), up to 30 fp	
		.,,	MPEG-4: VGA (640 × 480) / QVGA (320 × 240), up to 30 fps	
			JPEG (M-JPEG): 1,280 × 960 / VGA (640 × 480) / QVGA (320 × 240), up to 30 fp	
		Aspect ratio: [16:9]*3	H.264: 1,280 × 720 / 640 × 360 / 320 × 180, up to 30 fps	
			JPEG (M-JPEG): 1,280 \times 720 / 640 \times 360 / 320 \times 180, up to 30 fps	
	H.264/MPEG-4 *5 *6		Constant bitrate / Framerate priority / Best effort	
			1/3/5/7.5/10/12/15/20/30 fps	
		Bit Hate/Client	64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 1,536 / 2,048 / 3,072 /	
		Image Quality	4,096 / 8,192* kbps * H.264 mode only LOW / NORMAL / FINE	
		Refresh Interval		
			UNICAST / MULTICAST	
	JPEG	Image Quality	10 steps	
		Refresh Interval	0.1 fps ~ 30 fps	
		Transmission Type	PULL / PUSH	
	Audio Compi	ression	G.726 (ADPCM) 32 kbps / 16 kbps, G.711 64 kbps	
	Audio Mode		OFF / Mic (Line) input / Audio output / Interactive (Half duplex) / Interactive (Full duplex)	
	Authentication for Audio Total Bit Rate		Level 1 only / Level 2 higher / All users 64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 2,048 / 4,096 / 8,192 kbps / Unlimited	
	Supported P		184 / 128 / 256 / 384 / 512 / 768 / 1,024 / 2,048 / 4,096 / 8,192 kbps / Unlimited	
			IPv4: TCP/IP, UDP/IP, HTTP, HTTPS, RTSP, RTP, RTP/RTCP, FTP, SMTP, DHCP, DNS, DDNS, NTP,	
			SNMP, UPnP, IGMP, ICMP, ARP	
	FTP Client		Alarm image transmission, FTP periodic transmission (When the	
			FTP transmission is failed, backup on an optional SDHC/SD memory card is available.)	
	No. of Simultaneous Users		Up to 14 users (Depends on network conditions)	
	SDHC/SD Memory Card (Option)		H.264 recording: Manual REC / Alarm REC (Pre/Post) / Schedule REC	
			JPEG recording: Manual REC / Alarm REC (Post) / Backup upon network failure Compatible SD (SDHC) card: Panasonic 256 MB, 512MB, 1 GB, 2 GB, 4 GB*, 8 GB*, 16 GB*, 32 GB* mode	
			Companie 50 (SDHC) card: Panasonic 256 MB, 512MB, 1 GB, 2 GB, 4 GB, 6 GB, 16 GB, 32 GB mod *SDHC card	
	Face Detection		ON / OFF (with XML notification)	
	Cellular Phone Compatibility		JPEG image, AUX control (by access level)	
	Mobile Terminal Compatibility ⁷		iPad, iPhone, iPod touch (iOS 4.2.1 or later) Android™ mobile terminals	
Alarm	Alarm Source		1 terminal input, VMD, Command alarm	
	Alarm Actions		SDHC/SD memory recording, E-mail notification, Alarm terminal output,	
	Alarm Loc		Indication on browser, FTP image transfer, Panasonic protocol output	
	Alarm Log		With SDHC/SD memory card: 5,000 logs, without SDHC/SD memory card: 1,000 logs	
Input/ Output	Schedule Monitor Output (for adjustment)		Alarm / VMD / Access permission / H.264 recording/ Forcible black & white mode(WV-SW316L)	
mpuv Output			VBS: 1.0 V [p-p]/75 \(\Omega, NTSC composite, RCA Jack \) VBS: 1.0 V [p-p]/75 \(\Omega, PAL composite, RCA Jack \)	
	Microphone/Line Input		MIC IN and Line IN are selectable. ø3.5 mm stereo mini jack (monaural input) (Applicable microphone: Plug-in power type)	
			(monaurai input) (Applicable microphone: Plug-in power type) Supply voltage: 2.5 V ±0.5 V Input impedance: approx. 2 kΩ	
	Audio Output		ø3.5 mm stereo mini jack (monaural output) Line level	
	External I/O Terminals		ALARM IN, DAY/NIGHT IN, ALARM OUT, AUX OUT	
General	Safety/EMC	Standard	UL (UL60950-1), FCC (Part15 ClassA), CE	
General	Safety/EMC	Standard	DC (ICES003 ClassA) DC (ICES003 ClassA) CE (EN55022 ClassB, EN55024)	


TV System		NTSC	PAL	
General	Power Source and Power Consumption	12 V DC: 850 mA		
		* FOR UL LISTED MODEL(S), ONLY CONNECT 12 V DC CLASS 2 POWER SUPPLY.		
		PoE (IEEE 802.3af compliant) 48 V: 200 mA (Class 0 device)		
	Ambient Operating Temperature	-40 °C ~ +50 °C (-40 °F to 122 °F)		
	Ambient Operating Humidity	90 % or less (without condensation) IP66, IEC60529 measuring standard compatible 94 mm (W) × 89 mm (H) × 226 mm (L) (including projection of base cover fixing screw)		
	Water and Dust Resistance			
	Dimensions			
		(3-7/10" (W) × 3-1/2" (H) × 8-7/8" (L)) 1.4 kg (3.09 lbs.) Main body: Aluminum die cast/resin, metallic silver coating		
	Mass (approx.)			
	Finish			
		Front cover section clear part: Poly	carbonate resin	

- *1 For further information about PC system requirements and precautions for when using Microsoft Windows 7, Microsoft Windows Vista, or Windows Internet Explorer, click "Manual"-"Open" from the supplied CD-ROM and refer to "Notes on Windows / Internet Explorer versions".
 *2 When using IPv6 for communication, use Microsoft Windows 7 or Microsoft Windows Vista.
 *3 MPEG-4 is not supported. *4 [4 : 3] and [16 : 9] are alternative.
 *5 H.264 and MPEG-4 are alternative. *6 Transmission for 2 streams can be individually set in the


- The same can be individually set if the same can be individually set if the same compression method.

 The for information on the camera models of the supported operating systems, refer to our website at http://panasonic.net/pss/security/support/info.html.

Part Names and Functions



Appearance



- Trademarks and registered trademarks

 Microsoft, and Windows are registered trademarks of Microsoft Corporation in the U.S. and other countries.

 iPad, iPhone and iPod touch are registered trademarks of Apple Inc.

 UnilPhier is a registered trademark of Panasonic Corporation.

 "Super Dynamic", "SDII", "SDIII", "SDIII", "SDSIII", "SDSLIIN", "I-PRO" and "I-PRO SmartHD" logos are trademarks or registered trademarks of Panasonic Corporation.

 ONVIF and the ONVIF logo are trademarks of ONVIF Inc.
- All other trademarks identified herein are the property of their respective owners. Pandata that are definited in the property of their respective owners.

 Safety Precaution: carefully read the operating instructions and installation manual before using this product.
 Panasonic can not be responsible for network performance and/or other manufacturer products that reside on the network.

 Masses and dimensions are approximate.

- - Masses and dimensions are approximate.
 Specifications are subject to change without notice.
 These products may be subject to export control regulations.

DISTRIBUTED BY:

